
S500L-OSV-830 GAS MONITOR

Features

- Microprocessor based
- 4-20mA Analogue Output
- Voltage free relay contacts
- RS485 digital interface
- · Alphanumeric dot-matrix display
- "One Person" calibration
- Small size
- Certified ATEX II 2 G Exd IIC T6
- Low power consumption
- Standalone operation

The Monicon S500-OSV-830 is a self contained, intelligent gas sensor that offers a host of sophisticated features to provide fast, reliable warnings against concentrations of chlorofluorocarbon gases (CFC's) including R11, R12, R22 and R113.

The S500-OSV-830 will operate as a standalone instrument or in conjunction with a controller or a computer. The S500-OSV-830 is housed in an attractive, compact enclosure and may be configured or calibrated by one person, without declassifying the hazardous area. The gas concentration is indicated on a 4 character alphanumeric display which also indicates instrument status. The S500-OSV-830 is user programmable and no physical adjustments are necessary during calibration as the on-board computer assists the calibration procedure. All user variables are stored in non-volatile memory (EEPROM) and retained indefinitely even during total power failure.





Typical Applications for the S500L-OSV-830

- Chemical processing
- Chemical storage

MONICON

- Solvent storage
- Laboratories
- Plastics manufacture
- Packaging manufacture
- Insulation manufacture
- Refrigeration
- Aerosol manufacture

The S500-OSV-830 uses a semiconductor gas sensor combined with advanced, surface-mount microprocessor and firmware technology. Gases and vapours being adsorbed onto the surface of a heated semiconductor element causes the electrical resistance of the semiconductor to change. This resistance change is measured, processed and linearised by the on-board CPU to give a signal proportional to the gas concentration. A watchdog circuit monitors the system operation and resets the CPU if a failure is detected.

The S500-OSV-830 is calibrated or userprogrammed by activating the magnetic switches with a magnet. The operator is then guided through a variety of options by a user-friendly menu. The CPU constantly verifies system operation. In the unlikely event of a fault, the operator is alerted with a helpful diagnostic display.

S500L-OSV-830 Specifications

Supply voltage **Power consumption Circuit protection Transient Protection** Analogue output Analogue output load **Operating temperature** Storage temperature Humidity range **Preconditioning Requirements Full-Scale range Response time (T90)** Linearity Repeatability Resolution Sensor life Weight RS485 operating mode (optional) Max. units on RS485 loop **RS485** comm parameters RS485 error checking Unit interrogation time **Relay contacts Option setting** Alarm setting Alarm types **ATEX certification Recommended calibration flow rate** Mounting holes User variable storage **Electromagnetic Conformance (EMC) Cable gland entries Terminations Enclosure material**

Nominal 24Vdc (operates from 20Vdc to 35Vdc) 2W nominal. 2.3W maximum Electronic current limiter, 1.5A auto-reset PCB mounted, 3 Joule, Metal Oxide Varistor 4-20mA current source referenced to 0V 500 Ohms maximum -10°C to +40°C -40°C to +66°C 20%RH to 80%RH (Non-condensing) Operational: 30 seconds, Specification: 24 hours R22: 0-2000ppm, R113: 0-3000ppm, R11 & R12: 0-5000ppm Typically <60 seconds ±5% ±2% 2% Typically 3-5 years 2.0Kg (including sensor) Slave mode, half duplex, polled 100 1200-N-8-1 1 byte checksum 40mS SPST, NO, 125V @ 0A5 (30V DC @ 1A) each for A1 & A2 Digital setting (all options fitted as standard and user selectable) Digital setting (adjustable between 10% and 90% of full scale) Energised/de-energised. Enrichment/deficiency. User selectable II 2 G Exd IIC T6 Tamb -20°C to +60°C (Certificate number Baseefa 08ATEX0056) 500mL per minute 2 holes, diam 7mm, spaced 127mm Non-volatile RAM (EEPROM) Complies with EN50081 and EN50082 2 entries, each M20 x 1.5 PCB mounted terminal blocks to accept 1.5mm² cable Aluminium pressure die-casting, chromated with blue epoxy finish

